



Manual changeover switch

Introduction

A range of manual changeover switches, mounted in enclosures.

These are normally used to switch between mains and generator supply in conjunction with a manually operated (key or hand start) generator. However, they can be used to switch between any two supplies or to switch any single supply between two outputs.

All current ratings quoted are AC21 ratings @ 415v (40 degrees C).



Standard features (up to 100A)

- Rotary switch
- Thermoplastic/polycarbonate enclosure
- IP65 (IP54 with cable glands fitted)

Standard features (125A and above)

- "Load break style" switch built to IEC 947-3, EN60947-3, BS EN60947-3
- Door interlock with 3 position padlockable handle
- Load links or bridging bars fitted to switch
- Proprietary manufactured IP55 sheet steel enclosure with hinged, lockable front access door finished in grey RAL7032.
- Full internal screening
- Gland plates fitted top and bottom

Optional extras

- Auxiliary contacts
- Aluminium gland plates

Dimensions

	H	W	D
0-63A	225	225	100
100A	225	225	150
125-200A	500	400	250
250A	600	400	250
400-630A	800	600	400
800A	800	600	450
1000-1600A	1200	800	450
2500-3150A	1800	800	600

GENPART (UK) LTD

Tel: +44 (0)1953 882436

Fax: +44 (0)1953 885597

e-mail: sales@genpart.co.uk

<http://www.genpart.co.uk>

Unit 5, Threxton Road Industrial Estate, Watton, Thetford, Norfolk, IP25 6NG, England

E. & O. E.

We reserve the right to amend specifications without prior notice.

Issue 2 (24/01/02)